

DDJ-FLX2

COMPACT 2-CHANNEL
DJ CONTROLLER

- Compatible with multiple DJ applications
- Use with various music streaming services
- Smart CFX
- Smart Fader
- Lightweight and compact
- User-friendly features
- Performance Pads

 rekordbox

 djay

 serato DJ Lite


AlphaTheta



FREE YOUR INNER DJ

DDJ-FLX2 // COMPACT 2-CHANNEL DJ CONTROLLER

FREE YOUR INNER DJ



SPECIFICATIONS

Compatible Software	rekordbox for Mac/Windows rekordbox for iOS/Android djay Pro for Mac/Windows djay for iOS/Android Serato DJ Lite Serato DJ Pro – license needed	
Frequency Response	20 Hz - 20 kHz (USB)	
S/N Ratio	102 dB (USB)	
Total Harmonic Distortion	0.006 % (USB)	
Outputs	MASTER x 1 (3.5 mm stereo mini jack) PHONES x 1(3.5 mm stereo mini jack)	
USB	USB Type-C x 1	
Bluetooth®	Wireless system	Bluetooth Low Energy
	Maximum transmission distance	Approximately 10 m in unobstructed circumstances
	Frequency band	2.4 GHz
	Modulation method	FH-SS (Frequency hopping spread spectrum)
Power supply	USB bus power (When using the unit with mobile devices with ports other than USB Type-C, connect it via Bluetooth.)	
Power Consumption	DC 5 V, 500 mA	
Max. External Dimensions (W x D x H)	383.2 x 208 x 48.2 mm / 15.09" x 8.19" x 1.90"	
Main unit weight	1.2 kg / 2.6 lbs	
Accessories	USB cable (C to C) Warranty (for some regions) Quick Start Guide Precautions for Use	

rekordbox

Visit the official rekordbox website for the software's specifications: rekordbox.com

djay

Visit the official djay Pro website for the specifications of djay Pro: algoriddim.com

serato DJ Lite

Visit the official Serato website for the specifications of Serato DJ Lite: serato.com

PRODUCT FEATURES

rekordbox

djay

serato DJ Lite

Compatible with multiple DJ applications

The DDJ-FLX2 works with various DJ applications including rekordbox and djay. After installing your preferred app on your mobile device, you can connect to the controller and start DJing right away. And if you want to learn more advanced techniques, you can use DJ software on your PC/Mac, including Serato DJ Lite.



Smart Fader¹

Smart Fader automatically optimizes control of the volume, BPM, and bass – all you have to do is slide the crossfader in one direction. With this feature, you can easily mix tracks from different genres, even if they have vastly different tempos (BPM).

Apple Music

Beatport Streaming

Beatsource Streaming

SoundCloud Go+/DJ

TIDAL


Compatible with various music streaming services

Each DJ application is compatible with different streaming services, so you can choose one based on the music and DJ style you want to play (subject to availability in your country). If you go for djay, you can access Apple Music, allowing you to choose from over 100 million tracks and incorporate your favorite music into your mixes.




Lightweight and compact

The DDJ-FLX2 is AlphaTheta's lightest and most compact DJ controller, so, you can take it anywhere you want to play.



Smart CFX¹

Recreate complex and dynamic effect techniques with a simple turn of knob. You can use Smart CFX for connecting tracks together and for adding emphasis to the music whenever you like.



User-friendly features

With USB bus power, there's no need for an external power supply when you connect the unit to a PC/Mac or a mobile device² via USB Type-C. You can start DJing easily by playing music through the built-in speakers of your PC/Mac/mobile device, or you can plug speakers into the audio output terminals of the DDJ-FLX2.

1. Function names and operations may vary depending on the DJ application used. | 2. Except for some Android devices.

* Disclaimer: Specifications and price are subject to change. | rekordbox™ is a trademark or registered trademark of AlphaTheta Corporation. | djay, djay Pro, and Algoriddim are trademarks of Algoriddim GmbH, registered in the US and other countries. | Serato DJ Lite and Serato DJ Pro are registered trademarks of Serato Limited. | Other product, technology, and company names, etc. mentioned herein are trademarks or registered trademarks of their respective owners.

AlphaTheta

AlphaTheta EMEA Limited | Unit 39, Tileyard Studios, Tileyard Road, London, N7 9AH, UK | +44 (0) 203 761 7220
AlphaTheta Music Americas, Inc. | 2050 W. 190th Street, Suite 109, CA 90504, Torrance, USA | +1 (424) 488-0480
AlphaTheta Corporation | 6-F, Yokohama i-Mark Place, 4-4-5 Minatomirai, Nishi-ku, Yokohama, Kanagawa 220-0012 Japan | +81 045-522-5400



ALPHATHETA.COM